

## WIRELESS COMMUNICATION NETWORK FOR ENABLING INTERNET ACCESS

### TECHNICAL FIELD OF THE INVENTION

5 The present invention relates to the field of communication networks. More specifically, the present invention relates to wireless communication networks for transferring data packets between customer devices and the Internet.

### BACKGROUND OF THE INVENTION

10 The worldwide network of computers commonly referred to as the "Internet" has seen explosive growth in the last several years. The proliferation of the Internet, increased dependence on data, and a global trend toward deregulation of the telecommunications industry are driving efforts to satisfy a  
15 worldwide appetite for greater transmission capacity (i.e., bandwidth) and more efficient use of finite bandwidth. The phenomenon is particularly evident in the quest to alleviate the local loop bottleneck. The local loop bottleneck occurs where local-area networks (LANs), which link devices within a  
20 building or a campus, join to wide-area networks (WANs), which crisscross countries and hold the Internet together.

Advances in fiber technology have extended the capacity of WANs to trillions of bits per second. Meanwhile, LANs are evolving from ten megabits per second (Mbps) to gigabits per  
25 second. The local loop bottleneck has resulted because the connections between these two domains have not kept pace. That is, the vast majority of copper-wire circuits are limited to about the one and a half Mbps rate of a T1 digital transmission link. The typical home user faces a more extreme case of the  
30 same problem, with data moving between computer and the Internet about thirty times slower, through a modem and phone line operating at less than fifty-six kilobits per second.

EL72135807US

As the demand for connectivity increases, coupled with the expenses of installing a copper or fiber network and the data rate limitations of a wired network, the telecommunications industry has been compelled to look for alternative methods for achieving cost effective, high performance Internet access. One such technique is through the implementation of fixed wireless network for enabling Internet access.

Generally, a fixed wireless network includes a stationary transceiver at the home or business receiving the service. The transceiver is pointed toward a radio transmission tower to send and receive signals. The radio transmission tower can send and receive high-speed Internet data. A fixed wireless network is advantageous over conventional wired networks in that Internet service providers (ISPs) need not dig up city streets to install new cable or replace outdated, legacy copper loops. Moreover, an ISP can distribute Internet bandwidth without the entanglements of leasing or maintaining hard-wired connections or phone lines through the use of the fixed wireless network.

One technique employed in fixed wireless networks is a local multipoint distribution service (LMDS). LMDS is configured to deliver data through the air at rates of up to one hundred fifty-five Mbps. The high capacity of LMDS is possible because it operates in a large, previously unallocated expanse of the electromagnetic spectrum. Depending upon the local licensing regulations of a particular country, LMDS operates anywhere from two to forty-two gigahertz (GHz). Unfortunately, the licensing of this spectrum undesirably drives up the cost of the LMDS system. In addition, the costs of the transceivers of the LMDS system are cost prohibitive for small business and home applications.

Yet another problem exists with prior art fixed wireless networks. That is, many conventional fixed wireless networks are flat networks. Flat networks typically employ bridges, hubs, or OSI Layer 2 switches. A flat network is protocol-specific, relatively inexpensive, and moderately fast for low traffic levels. An exemplary, flat, fixed wireless network includes a wireless bridge at a cell site that communicates with a wireless bridge at a customer premise. The wireless bridge at the customer site is connected via wireline connection to a LAN network router, such as an Ethernet-to-Ethernet router. The LAN router is then connected to a junction of a LAN at the customer premise for routing packets through the customer LAN.

Due in part to the number of interconnected pieces at the customer premise, such a system is cost prohibitive for small business and home applications. In addition, the components at the customer premise are typically located indoors, with a coaxial cable directed from an antenna mounted to the roof-top of the premise into the building and connecting to the wireless bridge. Such a system requires a long radio frequency (RF) run to the roof-top antenna. Unfortunately, a long RF run drives the need for high power, more costly, radio signals due to signal losses in the cable. Furthermore, flat networks tend to be limited in terms of scalability (i.e., size they can grow to with respect to Internet Protocol traffic).

Another problem with flat networks is that each internetworking device shares the bandwidth. That is, flat networks suffer from transmission efficiency problems because upstream routing functions (such as prioritization) are performed at the cell sites, rather than at the customer premise. Such a scenario is problematic because the inefficient control of data packet transmission from customer

premises can lead to congestion and a high number of transmission errors caused by broadcast traffic on the flat network. This congestion and high number of transmission errors ultimately lowers the quality of service to the customer and decreases customer satisfaction.

Internet service providers do not offer multiple levels of service using the same wireless Internet access equipment. In other words, the flat Internet access networks currently offered by Internet service providers cannot accommodate both high priority, high speed users to low priority, low speed users while managing the problems of congestion caused by broadcast traffic since all users are sharing the bandwidth. This drives the need for customer specific hardware configurations at the customer premises and at the Internet access points for accommodating the level of priority-based routing and transmission speed desired by the customer. Customer specific hardware configurations undesirably drive up the cost of providing wireless Internet access in terms of hardware cost and deployment cost.

#### **SUMMARY OF THE INVENTION**

Accordingly, it is an advantage of the present invention that a communication network is provided for enabling customer devices access to the Internet.

Another advantage of the present invention is that the communication network facilitates the transfer of data packets between the customer devices and the Internet via wireless communication.

Another advantage of the present invention is that the network effectively accomplishes priority-based routing and bandwidth allocation at the customer premises.

Yet another advantage of the present invention is that the network includes cost effective, reconfigurable equipment at cell sites and customer premises.

The above and other advantages of the present invention are carried out in one form by a communication network for transferring data packets between customer devices and the Internet, the customer devices being located at customer premises. The network includes subscriber nodes located at the customer premises. Each subscriber node includes a router interconnected with the customer devices at the customer premise. A control node is in wireless communication with the subscriber nodes using a prescribed restricted frequency band, the prescribed restricted frequency band being used for transmitting the data packets. A network aggregation node is in communication with the control node for enabling transfer of the data packets between the customer devices and an Internet backbone.

#### **BRIEF DESCRIPTION OF THE DRAWINGS**

A more complete understanding of the present invention may be derived by referring to the detailed description and claims when considered in connection with the Figures, wherein like reference numbers refer to similar items throughout the Figures, and:

FIG. 1 shows a block diagram of a fixed wireless communication network for providing customer devices located at customer premises access to the Internet;

FIG. 2 shows a block diagram of an environment in which the fixed wireless communication network may be deployed;

FIG. 3 shows a perspective view of a subscriber node of the fixed wireless communication network of FIG. 1;

FIG. 4 shows a block diagram of a second unit of the subscriber node;

FIG. 5 shows a simplified block diagram of router in a first unit of the subscriber node;

5 FIG. 6 shows an exemplary Internet Protocol (IP) data packet; and

FIG. 7 shows a block diagram of an exemplary configuration of a control node of the fixed wireless communication network of FIG. 1.

#### **DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS**

FIG. 1 shows a block diagram of a fixed wireless communication network 20 for providing customer devices 22 located at customer premises 24 access to the Internet.

15 Communication network 20 is desirably deployed in a city-wide environment as a metropolitan area network (MAN). A MAN is a data network covering an area larger than a local area network (LAN), but less than a wide area network (WAN). A MAN typically interconnects two or more LANs, operates at a higher  
20 speed, may cross administrative boundaries, and may use multiple access methods. Communication network 20 may carry data, voice, video, image, and multimedia data. Fixed wireless communication network 20 will be referred to hereinafter as wireless MAN 20 to distinguish it from local area networks  
25 (LANs) and wide area networks (WANs), discussed below.

Wireless MAN 20 generally includes subscriber nodes 26, control nodes 28, a network aggregation center 30, and a network operations center 32. Subscriber nodes 26 are located at customer premises 24 and connect via a wired connection to  
30 customer devices 22.

Customer devices 22 are shown as local area networks (LAN A1, LAN A2, LAN An, LAN B1, and so forth), and subscriber nodes

26 desirably interconnect at a junction of these LANs. LANs are short distance data communications networks used to link computers and peripheral devices, such as printers, CD-ROMs, and modems, under some form of standard control. Customer  
5 devices 22 will be referred to hereinafter as LANs 22. LANs 22 may be located in businesses, schools, homes, and so forth.

Subscriber nodes 26 provide LANs 22 high-speed access to the Internet, in compliance with the IEEE 802.11 wireless LAN standard. The IEEE 802.11 wireless LAN standard places  
10 specifications on the parameters of both the physical (PHY) and medium access control (MAC) layers of the network. The PHY layer, which actually handles the transmission of data packets between nodes, can use either direct sequence spread spectrum, frequency-hopping spread spectrum, or infrared (IR) pulse  
15 position modulation. IEEE 802.11 supports data rates of 1, 2, 5.5, and 11 Mbps. In addition, IEEE 802.11 calls for operation in a restricted frequency band, in particular, the 2.4 - 2.4835 gigahertz (GHz) frequency band (in the case of spread-spectrum transmission), which is an unlicensed band for industrial,  
20 scientific, and medical (ISM) applications, and 300 - 428,000 GHz for IR transmission.

Control nodes 28 serve as cell sites in wireless communication with subscriber nodes 26 within MAN 20. Each of control nodes 28 is a wireless point of presence (WPOP). As  
25 known to those skilled in the art, a WPOP denotes a central facility or hub where subscribers are linked via wireless connection to access the Internet Service Provider's (ISP's) broadband backbone. A WPOP is advantageous over land line connectivity because it is high-speed (up to 11 Mbps versus a  
30 dial up connection or 1.544 Mbps T-1 line), it is reliable, it has low deployment cost relative to other last mile solutions, it is inexpensive to upgrade, there is no local telephone

company involvement, and it may be owned and managed by a single entity.

FIG. 2 shows a block diagram of an environment 34 in which fixed wireless communication network 20 (FIG. 1) may be deployed. Control nodes 28 provide radio frequency coverage over prescribed coverage areas, or sectors 36, of cells 38. Control nodes 28 utilize IEEE 802.11 compliant equipment and desirably have a 5-10 mile radius of coverage. Thus, subscriber nodes 26, located at customer premises 24 (FIG. 1), are located within one of sectors 36 managed by one of control nodes 28. Subscriber nodes 26 communicate with particular ones of control nodes 28 using a prescribed restricted frequency band in the unlicensed ISM band.

Environment 34 is shown with only three of cells 38 for clarity of illustration. However, it should be understood that environment 34 may be subdivided into any number of cells 38 in order to provide city-wide or near city-wide radio frequency coverage using wireless MAN 20 (FIG. 1). Likewise, each of cells 38 is subdivided into three of sectors 36 for clarity of illustration. However, cells 38 may be subdivided into more or less sectors 36 in response to a quantity of users of wireless MAN 20 (FIG. 1) in a particular region and their desired level of service (discussed below). Thus, wireless MAN 20 (FIG. 1) can be scaled to accommodate the actual, or projected, number of users and their level of service within environment 34.

Referring back to FIG. 1, a direct sequence signaling technique can divide the 2.4 GHz ISM band into fourteen channels each having a bandwidth of twenty-two MHz. Adjacent channels overlap one another partially, with three of the fourteen being completely non-overlapping. As shown in wireless MAN 20, subscriber nodes 26, labeled A1, A2, through An, are in communication with one of control nodes 28, labeled



CONTROL NODE 1, via a first frequency 40, labeled MAN NETWORK  
FREQUENCY A, of the 2.4 - 2.4835 gigahertz ISM band. Likewise,  
subscriber nodes 26, labeled B1, B2, through Bn, are in  
communication with the one of control nodes 28, i.e., CONTROL  
5 NODE 1, via a second frequency 42, labeled MAN NETWORK  
FREQUENCY B, of the ISM band. Subscriber nodes 26, labeled C1,  
C2, through Cn, are in communication with the one of control  
nodes 28, i.e., CONTROL NODE 1, via a third frequency 44,  
labeled MAN NETWORK FREQUENCY C, of the ISM band.

10 In an exemplary embodiment, control node 28, labeled  
CONTROL NODE 1, is configured to transmit using one of first,  
second, and third frequencies 40, 42, and 44 in each sector 36  
(FIG. 2) of a particular one of cells 38 (FIG. 2) for which  
control node 28 provides radio frequency coverage. However,  
15 since first, second, and third frequencies 40, 42, and 44 are  
non-overlapping, control node 28 may be configured to transmit  
using two or three of frequencies 40, 42, and 44 in each sector  
36 (FIG. 2) for which control node 28 provides radio frequency  
coverage. Thus, wireless MAN 20 (FIG. 1) can be further scaled  
20 to accommodate the actual, or projected, number of users and  
their level of service within environment 34.

Only a few of subscriber nodes 26 are shown for clarity of  
illustration in FIG. 1. However, ellipses indicate that any  
quantity of subscriber nodes 26 may be included, limited in  
25 number by quality of service and bandwidth prioritization  
considerations, discussed below. In addition, only a few of  
control nodes 28 are shown for clarity of illustration.  
However, an ellipsis between control nodes 28 indicates that  
any quantity of control nodes 28 may be included for providing  
30 city-wide or near city-wide coverage by wireless MAN 20.

Control nodes 28 connect to a backbone 46 of wireless MAN  
20. MAN backbone 46 is an aggregate of high-speed wired and

wireless connections that forms a major pathway within wireless MAN 20. MAN backbone 46 joins control nodes 28 in communication with network aggregation center 30 and network operations center 32. Network aggregation center 30 is in communication with an Internet Service Provider (ISP) backbone 48 and/or an Internet backbone 50 for enabling the transfer of data packets (discussed below) between customer devices 22 and Internet backbone 50. Network operations center 32 generally monitors the status of wireless MAN 20, supervises and coordinates wireless MAN 20 maintenance, and accumulates accounting, usage data, and user support.

As will become readily apparent in the following discussion, wireless MAN 20 is configured to efficiently manage communication traffic between subscriber nodes 26 and Internet backbone 50 in response to a predetermined level of service for each of subscriber nodes 26.

FIG. 3 shows a perspective view of one of subscriber nodes 26 of wireless MAN 20 (FIG. 1) at one of customer premises 24. Subscriber node 26 is configured as an interface between one of LANs 22 and one of control nodes 28 (FIG. 2). Subscriber node 26 generally includes an antenna 52, a first unit 54, a second unit 56, a cable 58 interconnecting first unit 54 and second unit 56, and a network hub 60 coupled between second unit 56 and a junction 62 of LAN 22. For clarity of illustration, LAN 22 is arranged in a bus topology and employs an Ethernet media-access control method.

In a preferred embodiment, antenna 52 is a grid antenna suitable for directional 2.4 GHz ISM band applications. Antenna 52 desirably provides a predetermined gain and a predetermined beam-width for optimal communication between subscriber node 26 and control node 28 (FIG. 1). A grid antenna is desirable for use at subscriber node 26 because it

is nearly undetectable in most installations, it is durable, and it can be installed for either vertical or horizontal polarization. A grid antenna may also include a built-in tilt mechanism that allows installation at various degrees of  
5 incline for easy alignment. Although antenna 52 is described in terms of a grid antenna, it should be understood that other types of antennas may alternatively be employed for directional 2.4 GHz ISM band application.

A mast 64 of antenna 52 is mounted to an external portion  
10 of customer premise 24. For example, anchors 66 secure mast 64 to a parapet 68 of customer premise 24. First unit 54 is located proximate antenna 52 and external to customer premise 24. In this exemplary embodiment, first unit 54 is mounted to mast 64. As such, a housing of first unit 54 is desirably  
15 manufactured from a durable, weather resistant material. The components of first unit 54 will be described below in connection with FIG. 5.

A coaxial cable 70 is directed between antenna 52 and first unit 54 for conveying radio frequency signals in the 2.4 GHz  
20 ISM band between antenna 52 and first unit 54. Coaxial cable 70 may include a reverse polarity threaded nut coupling (TNC) connector for connection to first unit 54. In a preferred embodiment, first unit 54 is located proximate antenna 52 so that coaxial cable 70 is as short as possible, for example,  
25 less than two feet long. By configuring coaxial cable 70 to be very short, signal strength loss of the radio frequency signals conveyed by coaxial cable 70 is minimized. Since little signal strength is lost through coaxial cable 70, a radio frequency signal can be transmitted at relatively low power, thus,  
30 decreasing costs associated with high power transmission and decreasing the potential for interference.

Cable 58 has a first end 72 connected to first unit 54. In an exemplary embodiment, first end 72 includes a watertight connector, for example, NEMA 4X standard connector, for coupling to a receptacle on first unit 54. A second end 74 of cable 58 is routed through a penetration location 76 into the inside of customer premise 24. Second end 74 of cable 58 does not include a connector, so that the size of penetration location 76 may be kept as small as possible. Second end 74 is coupled to second unit 56.

Cable 58 is desirably manufactured from a durable, weather resistant material to withstand exposure to wind, moisture, and sun. For example, cable 58 may be ultraviolet (UV) rated category five (Cat 5) cable. Cat 5 cable is typically unshielded twisted pair, containing four twisted wire pairs. Two of these pairs are used for 100 Mbps (100Base-T) and 10 Mbps (10Base-T) Ethernet applications, leaving two pairs unused.

FIG. 4 shows a block diagram of second unit 56 of the subscriber node 26 (FIG. 3). Second end 74 of cable 58 is coupled to second unit 56 using a conventional telecommunications type punch down connector 78. A first twisted wire pair 80 and a second twisted wire pair 82 of cable 58 are coupled to connector 78. First and second twisted wire pairs 80 and 82, respectively, are subsequently in communication with a data port 84 of second unit 56. Communication between pairs 80 and 82 and data port 84 may be achieved, for example, via traces 86 on a printed circuit board of second unit 56.

A third twisted wire pair 88 of cable 58 is in communication with a power input 90 of second unit 56. This communication between third twisted wire pair 88 and power input 90 may be achieved, for example, via traces 92 on the

second unit 56 printed circuit board. A fourth twisted wire pair 94 may be optionally utilized to carry signaling information to light emitting diodes (LEDs) 96 on second unit 56 reserved to indicate subscriber node 26 and/or network status. This communication between fourth twisted wire pair 94 and LEDs 96 may be achieved, for example, via traces 98 on the second unit 56 printed circuit board.

Referring to both FIGs. 3-4, an Ethernet cable 100 is coupled between data port 84 and network hub 60. Ethernet cable 100 conveys data packets (discussed below) between traces 86 of second unit 56 and LAN 22. Due to the interconnection of traces 86 with first and second twisted wire pairs 80 and 82, respectively, at connector 78, these data packets are conveyed between second unit 56 and first unit 54.

A power cable 102 is coupled between power input 90 and a power transformer 104 connected to a conventional alternating current (AC) wall socket 106 at customer premise 24. Power transformer 104 converts the provided AC power into a direct current (DC) power. This DC power is conveyed to traces 92 of second unit 56. Due to the interconnection of traces 92 with third twisted wire pair 88 at connector 78, DC power is subsequently supplied to first unit 54.

Accordingly, cable 58 conveys data packets between LAN 22 and first unit 54. In addition, cable 58 carries DC power to energize the components (discussed below) of first unit 54. This single cable configuration simplifies the hardware configuration of subscriber node 26 and decreases installation time since only one cable is routed rather than separate cables for power and data. In addition, the size of penetration location 76 is advantageously minimized since only one cable is used, rather than two separate cables.

FIG. 5 shows a simplified block diagram of a router 108 in first unit 54 (FIG. 3) of subscriber node 26 (FIG. 3). Router 108 is interconnected with LAN 22 via cable 58 (FIG. 3) and second unit 56 (FIG. 3). Router 108 performs bridging and routing functions. That is, router 108 performs the conventional bridging functions of accepting data packets from control nodes 28 and forwarding them to LAN 22 (FIG. 3). In addition, router 108 performs routing functions of accepting data packets from LAN 22 and routing them to one of control nodes 28.

Routing functions, such as establishing data connectivity with a WAN, bandwidth allocation, and data packet prioritization are typically performed at the wireless point of presence (WPOP) in fixed wireless communication networks. Router 108 of subscriber node 26 (FIG. 3) advantageously performs these routing functions at customer premise 24 (FIG. 3) to provide LAN 22 (FIG. 3) access to the Internet.

The use of router 108 at each of subscriber nodes 26 (FIG. 1) allows routing decisions to be made based upon a desired level of service related to specific subscriber nodes 26 and current traffic loads over the ISM band used for communication between subscriber nodes 26 and control nodes 28 (FIG. 1). Through the use of router 108 at each of subscriber nodes 26, overall network efficiency increases thereby increasing customer satisfaction.

In general, router 108 includes a power regulator 110, an Ethernet data interface 112, a single board computer 114, a radio frequency module 116, and a serial interface 118 all of which are interconnected via a backplane 120. In addition, radio frequency module 116 is coupled to antenna 52 via coaxial cable 70.

As discussed previously, cable 58 is a Cat 5 cable containing four twisted wire pairs. Third twisted wire pair 88, carrying DC power from second unit 56, is coupled to power regulator 110. Power regulator 110 regulates the DC power received from second unit 56 via third twisted wire pair 88 of cable 58 to mitigate transients in the received DC power. For example, power regulator 110 serves to regulate and step down a received power from 12-24 volts DC to 3-5 volts DC. This power is subsequently delivered to other components within second unit 54 via backplane 120.

First and second twisted wire pairs 80 and 82, respectively, of cable 58 are coupled to Ethernet data interface 112 for conveying data packets (discussed below) between router 108 and the interconnected LAN 22 (FIG. 3). In a preferred embodiment, Ethernet data interface 112 is a commercial off-the-shelf (COTS) Ethernet card CompactFlash Type 1 form factor configured to fit in a Type 1 or Type 2 Personal Computer Memory Card International Association (PCMCIA) PC interface slot on single board computer 114 or alternatively on backplane 120.

Single board computer 114 is a COTS circuit board that typically contains a microprocessor, ROM and RAM, serial I/O lines, and parallel I/O ports. Single board computer 114 serves as the main processing unit or controller for router 108. In a preferred embodiment, single board computer 114 is a 486CORE module manufactured by Compulab, Haifa, Israel. The 486CORE module is an embedded PC-compatible single board computer designed to serve as a building block in applications' design. It should be understood, however, that a number of existing and upcoming COTS single board computers are equivalently suitable to serve as single board computer 114.

Single board computer 114 employs an open source computing platform. In other words, single board computer 114 is programmed via serial interface 118 using open source software. Open source software is advantageous because it is freely distributed along with its source code. The source code can be changed readily so that the program stored in single board computer 114 can be altered to add advanced routing features.

In a preferred embodiment, Linux is employed in single board computer 114 as the open source software. Linux is a full-featured, powerful, and robust Unix operating system. Through the use of the Linux open source software, router 108 is configured to establish data connectivity (i.e., interface) between control nodes 28 (FIG. 1) and subscriber nodes 26 (FIG. 1) and to achieve isolation between subscriber node 26 and the rest of wireless MAN 20 (FIG. 1). In addition, the Linux open source software is used to manage bandwidth between subscriber node 26 (FIG. 3) and control node 28 in order to fairly share bandwidth of the ISM band between subscriber nodes 26 and control node 28 (FIG. 1).

Accordingly, single board computer 114 utilizes the routing capabilities provided through the execution of a program that employs a Linux open source computing platform to configure and enable the transmission of data packets (discussed below) from antenna 52 via radio frequency module 116. Radio frequency module 116 is a COTS transceiver suitable for the 2.4 GHz ISM band applications for sending and receiving data packets. In addition, radio frequency module 116 includes collision detection capability for the detection of simultaneous transmissions that can result in transmission errors.

FIG. 6 shows an exemplary Internet Protocol (IP) data packet 122, also known to those skilled in the art as an IP datagram. IP data packet 122 is the fundamental unit of



information passed across the Internet. IP data packet 122 includes, among other things, a header 124 and data 126. Header 124 contains control information such as a source address 128, a destination address 130, a packet length 132, a type of service octet 134, and other control information 136, such as synchronizing bits. Data 126 is the payload or text to be transmitted.

Router 108 (FIG. 5) manages bandwidth allocation for the transmission of IP data packet 122 over the ISM band and manages the transmission priority of IP data packet 122. The management of bandwidth allocation entails the provision of varying levels of throughput of IP data packets 122 based on a predetermined level of service for subscriber node 26 (FIG. 3). Likewise, the management of transmission priority entails setting a transmission priority for each of a number of IP data packets 122 in response to the predetermined level of service. The transmission priority ultimately affects the order, or sequence, in which IP data packets 122 are transmitted from a number of subscriber nodes 26 (FIG. 1) using the same one of first, second, and third frequencies 40, 42, and 44, respectively (FIG. 1).

Router 108 manages bandwidth allocation and prioritization by setting, or altering, type of service octet 134 for each IP data packet 122 received by router 108 from LAN 22 (FIG. 3). Type of service octet 134 includes a precedence field 138, a type of service (TOS) field 140, and an MBZ (must be zero) field 142. Precedence field 138 is used to denote the importance or priority of IP data packet 122. Type of service field 140 is used to denote how wireless MAN 20 (FIG. 1), including router 108, should make tradeoffs between throughput, delay, reliability, and cost. MBZ field 142 is typically unused and set to zero.

Router 108 sets the three bits of precedence field 138 to affect prioritization of the transmission of IP data packet 122 through wireless MAN 20 (FIG. 1). In an exemplary embodiment of the present invention, wireless MAN 20 may include three  
5 levels of prioritization, i.e., precedence. These three levels may include a priority 1 (P1) level of service. P1 service is equivalent to point-to-point broadband connectivity typically offered on a wired medium. A P1 level of service is intended for businesses with significant data requirements, and may have  
10 a performance equivalent to T-1 (1.544 Mbps), E-1 (2.048 Mbps), T-3 (44.736 Mbps), DS-3 (44.736 Mbps), and so forth.

A second level of service may include a priority 2 (P2) level of service. P2 service communication traffic yields to P1 service communication traffic. That is, P2 traffic has a  
15 lower transmission priority than P1 traffic. A P2 level of service is intended for small to medium sized businesses and/or residential customers, and is comparable to Symmetrical DSL (1 Mbps, both ways) services.

A third level of service may include a priority 3 (P3) level of service. P3 service communication traffic yields to both P1 and P2 service communication data traffic. That is, P3  
20 traffic has a lower transmission priority than both P1 and P2 traffic. A P3 level of service is intended for home-based consumers, but offers burst downloads. As a result, P3 service exceeds conventional cable modem transmission speed.  
25

Although the present invention is described in terms of three levels of service, it should be understood that through the use of the Linux open source computing platform, an Internet Service Provider (ISP) may utilize precedence field  
30 138 of IP data packet 122 to distinguish a number of levels of service, in accordance with ISP preferred transmission rates and billing schedules.

Router 108 may set the four bits of TOS field 140 to affect tradeoffs between throughput, delay, reliability, and cost. By way of example, bits of TOS field 140 may be set as shown in the following TOS bit table:

5

TOS BIT TABLE	
TOS VALUE	REQUESTED TOS
1000	minimize delay
0100	maximize throughput
0010	maximize reliability
0001	minimize monetary cost
0000	normal service

10

Accordingly, varying levels of service can be set for each of subscriber nodes 26 (FIG. 1) through the setting of precedence field 138 and TOS field 140 of type of service octet by router 108. These varying levels of service allow wireless MAN 20 to provide a segmented system that can accommodate both high priority, high speed subscribers and low priority, low speed subscribers using the same equipment, i.e., subscriber node 26 (FIG. 5).

15

20

Such a segmented system is advantageous to the Internet Service Provider because the ISP can charge varying rates, depending upon the desired level of service. Likewise, a segmented system is advantageous to the subscriber because the subscriber can decide which level of service is preferred, hence, pay for and receive that desired level of service. In addition, the hardware configuration at each of subscriber nodes 26 (FIG. 1) is the same regardless of the desired level of service. Moreover, the hardware configuration is based on COTS components. A common hardware configuration based on COTS

components results in lower deployments costs of MAN 20 (FIG. 1).

Router 108 (FIG. 5) configures the transmission priority of IP data packets 122 (FIG. 6) by setting type of service octet 134 (FIG. 6) in response to a predetermined level of service for subscriber node 26 (FIG. 1). In addition, router 108 allocates bandwidth over a particular one of first, second, and third frequencies 40, 42, and 44 (FIG. 1) in accordance with the predetermined level of service. Router 108 also establishes connectivity with one of control nodes 28.

When one of control nodes 28 receives an IP data packet, such as IP data packet 122 (FIG. 6), from one of subscriber nodes 26 (FIG. 1), control node 28 accesses type of service octet 134 (FIG. 6) to determine the transmission priority of IP data packet 122. Control node 28 then employs the transmission priority set in precedence field 138 (FIG. 6) and the preferred type of service set in TOS field 140 (FIG. 6) to facilitate transfer of IP data packet 122 onto MAN backbone 46 in order to forward IP data packet 122 to network aggregation center 30 (FIG. 1).

FIG. 7 shows a block diagram of an exemplary configuration of one of control nodes 28 of fixed MAN 20 (FIG. 1). Control node 28 includes a plurality of control node routers 144 and a plurality of directional antennas 146. One each of control node routers 144 is in communication with one each of directional antennas 146. A control node backbone 148 is in communication with each of control node routers 144 and network aggregation node 30 via MAN backbone 46.

As discussed previously, control node 28 provides radio frequency coverage over a prescribed coverage area, or cell 38 (FIG. 2). Furthermore, cell 38 is subdivided into a number of sectors 36 (FIG. 2). Each pair of control node routers 144 and

directional antennas 146 desirably provides radio frequency coverage over one of sectors 36 using one of first, second, and third frequencies 40, 42, and 44, respectively (FIG. 1).

In a preferred embodiment, control node routers 144 are substantially identical to router 108 (FIG. 5). Likewise, directional antennas 146 are substantially identical to directional antenna 52 (FIG. 3). Accordingly, cost savings is achieved in the deployment of control nodes 28 by utilizing circuitry that is common to subscriber nodes 26 (FIG. 1).

Furthermore, by using a control node router 144/directional antenna pair 146 for each ISM frequency used in each of sectors 36 (FIG. 2), control node 28 is readily scaled to accommodate the actual, or projected, number of users and their level of service within one of cells 38 of environment 34 (FIG. 2).

In summary, the present invention teaches of a fixed wireless communication network using the ISM frequency band for enabling customer devices access to the Internet. The wireless communication network facilitates the transfer of data packets between the customer devices and the Internet through the use of a router located at each customer premise and interconnected with the customer devices. The router employs an open source computing platform for enabling full routing capabilities at the subscriber nodes. In particular, the router performs priority-based routing of IP data packets and bandwidth allocation for the IP data packets at the customer premise, thereby, alleviating the problems of congestion and transmission errors caused by broadcast traffic on prior art flat networks. In addition, the fixed wireless network includes a common hardware configuration using COTS components at each subscriber node and at the control nodes which results in a cost effective, scalable, and readily deployed system.

Although the preferred embodiments of the invention have been illustrated and described in detail, it will be readily apparent to those skilled in the art that various modifications may be made therein without departing from the spirit of the invention or from the scope of the appended claims. The  
5 specification and drawings are, accordingly, to be regarded in an illustrative rather than restrictive sense.

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2